



Wireless Tuner WT-5800



- Phase Locked Loop (PLL) synthesis operation
- 64 selectable channels
- True diversity technology
- Double super-heterodyne receiving system
- Two-line LCD display
- Auto mixing input function
- Squelch function (carrier, noise, tone)
- Usable frequencies scanning and vacant channel search function
- Compact half-rack size body
- 6 points audio level meter for microphone sensitivity adjustment
- Compander circuitry for minimizing ambient noise
- Antenna distribution output
- Whip antenna x 2
- Low-battery indicator (wireless microphone's battery voltage becomes low)

Wireless Tuner WT-5805



- Phase Locked Loop (PLL) synthesis operation
- 64 selectable channels
- TOA space diversity technology
- Double super-heterodyne receiving system
- Two-line LCD display
- Auto mixing input function
- Squelch function (carrier, noise, tone)
- Usable frequencies scanning and vacant channel search function
- Compact half-rack size body
- 6 points audio level meter for microphone sensitivity adjustment
- Compander circuitry for minimizing ambient noise
- Whip antenna x 2
- Low-battery indicator (wireless microphone's battery voltage becomes low)

Wireless Tuner WT-5810



- Phase Locked Loop (PLL) synthesis operation
- 16 selectable channel frequencies
- TOA space diversity technology
- Double super-heterodyne receiving system
- Auto mixing input function
- Squelch function (carrier, noise, tone)
- Usable frequencies scanning and vacant channel search function
- Compact portable design
- Compander circuitry for minimizing ambient noise
- Rod antenna x 2
- Balanced output (XLR connector) and phone jack output
- Low-battery indicator (wireless microphone's battery voltage becomes low)

2-Channel Wireless Tuner WT-4820



- 16 selectable channel frequencies
- Antenna cascade output function (parallel connection possible for linking two WT-4820 units)
- TOA space diversity technology
- Auto mixing input function
- Tuner unit connections accessible from the front (even if rack mounted, the front panel is easily opened)
- Mix output/tuner 1 output (selectable); tuner 2 has 2 outputs
- Whip antenna x 2
- Compact half-rack size body
- External antenna input

Power/Antenna Distributor WD-5800



- 2 antenna inputs and 4 distributed outputs
- 2 inputs per antenna which are mixed for output (when 2 antenna are set up in a large room)
- Supplies power to antenna
- Compact 19" rack-mount design

UHF Wireless Tuner Unit WTU-4800



- PLL synthesis double super-heterodyne diversity tuner module
- Squelch function mutes output to reduce noise
- Includes compander noise reduction to cut ambient RF noise

Rechargeable Battery WB-2000-2



- AA nickel-metal hydride (Ni-MH) rechargeable battery
- For Wireless Microphones, Wireless Transmitter and Portable Receiver

Battery Charger BC-5000-12



- Number of wireless microphones to be charged simultaneously: 12
- Fully charges within 3 hours

Battery Charger BC-5000-6



- Number of wireless microphones to be charged simultaneously: 6
- Fully charges within 3 hours

Battery Charger BC-5000-2



- Number of wireless microphones to be charged simultaneously: 2
- Fully charges within 3 hours

AC Adapter AD-5000-6 / AD-5000-2



- AD-5000-6: For BC-5000-12 and BC-5000-6 battery chargers
- AD-5000-2: For BC-5000-2 battery charger

UHF Wireless Antenna YW-4500



- UHF wireless dipole indoor antenna
- Wall mounted
- Power supplied by tuner unit (WT-5800 / WT-5805 / WT-4820) through coaxial cable
- Built-in RF signal booster
- Attenuation switch helps minimize noise and any interference

Options

Waist Pouch WH-4000P



Windscreen WH-4000S



- Contains 10 pieces

Earphone Pad YP-E401PAD01



- Contains 100 pieces

Rack Mount Bracket Kit MB-WT3



- For rack mounting one WT-5800, WT-5805 and/or WT-4820 unit

Rack Mount Bracket Kit MB-WT4



- For rack mounting two WT-5800, WT-5805 and/or WT-4820 unit

Rack Mount Bracket MB-15B



- For rack mounting one WD-5800

Specifications

Wireless Microphones & Microphones



WM-5420



WM-5270



WM-5265



WM-5225

Microphone Element	Dynamic microphone: Cardioid	Dynamic microphone: Unidirectional	Dynamic microphone: Cardioid	Electret condenser microphone: Unidirectional
Frequency Range	636 - 806 MHz, UHF	576 - 865 MHz ^{*1} , UHF		
Channel Selectable	64 channels ^{*1}			
Maximum Input Level	132 dB SPL	142 dB SPL	132 dB SPL	126 dB SPL
Battery	LR6 (AA)	LR6 (AA)	LR6 (AA) or WB-2000 (Ni-MH battery)	(AA) or WB-2000 (Ni-MH battery)
Finish	ABS Resin, coating	Metal, Dark Grey	Resin, coating	Resin, coating
Dimensions	74 (W) x 184 (H) x 20 (D) mm	Φ 48 x 244 mm	Φ 50 x 229 mm	Φ 43.6 x 231.5 mm
Weight	105 g (with battery)	340 g (with battery)	205 g (with battery)	180 g (with battery)
Accessories	Clip, Neck strap, Screw driver	Microphone holder (with stand adapter), Storage case, Rolling stopper	Microphone holder (with stand adapter), Storage case, Screw driver	Microphone holder (with stand adapter), Storage case, Screw driver



YP-M5300



YP-M5310



WH-4000A



WH-4000H

Microphone Element	Electret condenser microphone: Unidirectional	Electret condenser microphone: Omnidirectional	Electret condenser microphone: Unidirectional	Electret condenser microphone: Unidirectional
Sensitivity	-63 dB ±3 dB (0 dB=1V/0.1 pa. 1kHz)	-64 dB ±3 dB (0 dB=1V/0.1 pa. 1kHz)	-66 dB ±3 dB (0 dB=1V/0.1 pa. 1kHz)	-66 dB ±3 dB (0 dB=1V/0.1 pa. 1kHz)
Frequency Response	100 Hz - 12,000 Hz	100 Hz - 15,000 Hz	-	-
Maximum Input Level	120 dB SPL	110 dB SPL	120 dB SPL	120 dB SPL
Cord Length	1.3 m			
Connector	Φ 3.5 mm mini plug			
Finish	Dark Black	Dark Black	Headband: EVA, black Frame: Stainless, black (Silicon rubber) Gooseneck: Black (shrink tube)	Frame: Stainless, black (Silicon rubber) Gooseneck: Black (shrink tube)
Weight	20 g (cable included)		50 g (cable included)	



YP-M5000E



YP-M5000H

Microphone Element	Electret condenser microphone: Omnidirectional	
Frequency Response	20 Hz - 20,000 Hz	
Sensitivity	-67 dB ±3 dB (0 dB=1V/0.1 pa. 1kHz)	
Maximum Input Level	115 dB SPL, 1 kHz at 1%	
Cord Length	1.3 m	
Connector	Φ 3.5 mm stereo plug	
Finish	Beige color	
Weight	14 g (cable included)	21 g (cable included)

Wireless Transmitter



WM-5325

Microphone Element	-
Frequency Range	576 - 865 MHz ^{*1} , UHF
Channel Selectable	64 channels ^{*1}
Maximum Input Level	-14 dB to -29 dB* (Audio level control: Min. to Max.)
Battery	LR6 (AA) or WB-2000 (Ni-MH battery)
Finish	Resin, coating (change other's)
Dimensions	62 (W) x 102.5 (H) x 23 (D) mm
Weight	90 g (with battery)
Accessories	Screw driver, Storage case, Neck Strap
Option	Ni-MH battery: WB-2000

Portable Receiver



WT-5100

Receiving Frequencies	UHF band (16 ch)
Receiving System	Double super-heterodyne
Receiving Sensitivity	Better than 60 dB Signal to Noise ratio (20 dBμV input, ±40 kHz deviation)
Frequency Response	200 Hz - 5 kHz (Portable transmitter to Portable receiver)
Battery	LR6 (AA) or WB-2000 (Ni-MH battery)
Finish	Resin, dark silver
Dimensions	62 (W) x 163.6 (H) x 32.5 (D) mm
Weight	125 g (with battery)
Accessories	Neck Strap x 1
Options	Ni-MH battery: WB-2000, Assist Earphone: YP-E5000, Ear-suspension Earphone: YP-E401

Wireless Tuners



	WT-5800	WT-5805	WT-5810	WT-4820
Power Requirement	AC mains (AC Adapter must be used)			
Frequency Range	576 - 865 MHz* ¹ , UHF			576 - 865 MHz* ¹ , UHF (WTU-4800)
Channel Selectable	64 selectable frequencies		16 channels	
Receiving System	Double super-heterodyne			Double super-heterodyne (WTU-4800)
Diversity System	True diversity	Space diversity	Space diversity	Space diversity (WTU-4800)
Mixing Output	MIC: -60 dB* ² , 600Ω, balanced, XLR-3-31 type connector LINE: -20 dB* ² , 600Ω, unbalanced, phone jack*			-
Mixing Input	-20 dB* ² , 10kΩ, unbalanced, phone jack			
Antenna	Whip antenna		Rod antenna	Whip antenna
Antenna Input	75Ω, BNC, 9 V DC	75Ω, BNC, 9 V DC	-	75Ω, BNC, 9 V DC
Antenna Output	75Ω, BNC (Gain 0 dB)	-	-	75Ω, BNC (Gain 0 dB)
Receiving Sensitivity	90 dB or more			80 dB or more (WTU-4800)
Squelch Sensitivity	18 - 40 dBμ V variable			18 dBμ V (WTU-4800)
Tone Frequency	32.768 kHz			-
S/N Ratio	110 dB or more (A-weight, unbalanced output)		104 dB or more (A-weight, unbalanced output)	102 dB or more (A-weight, balanced output)
Harmonic Distortion	1% or less (typical)			
Frequency Response	100 Hz - 15,000 Hz, ±3 dB			50 Hz - 18,000 Hz, ±3 dB
Finish	Resin, black			
Dimensions	210 (W) x 44 (H) x 205.1 (D) mm		206 (W) x 40.6 (H) x 152.7 (D) mm	210 (W) x 44.2 (H) x 181 (D) mm
Weight	700 g	700 g	590 g	770 g (without tuner module)

*1 The number of channels may differ from country to country.

*2 0 dB = 1V

Battery Chargers



	BC-5000-12	BC-5000-6	BC-5000-2
Power Requirement	12 V DC (optional AC Adapter AD-5000-6 must be used)		12 V DC (optional AC Adapter AD-5000-2 must be used)
Power Consumption	4.4 A	2.2 A	700 mA
Charging Time	Max. 3h		
Number of Wireless Microphone to be Charge simultaneously	12	6	2
Finish	Case: Steel plate, black, paint Microphone receptacle section: ABS resin, black		Case: Steel plate, black, paint Microphone receptacle section: PPE resin, black
Dimensions	390 (W) x 118 (H) x 246 (D) mm	390 (W) x 118 (H) x 131 (D) mm	238 (W) x 105 (H) x 98 (D) mm
Weight	3.4 kg (with mounting adapters)	2 kg (with mounting adapters)	500 g (with mounting adapters)
Accessories	Mounting adapter x 12	Mounting adapter x 6	Mounting adapter x 2

* Using the mounting adapter allows one each of the WM-5225, WM-5265, WM-5325, WT-5100 to be charged in combination.

Earphones



	YP-E401
Type	Dynamic type
Impedance	16Ω
Frequency Range	300 Hz - 15 kHz
Input	Max. 50 mW
Terminal	Φ 3.5 mm mini plug (3-pole)
Finish	Black
Weight	17 g
Accessories	Ear-pad x 1, Suspension ring x 2

UHF Wireless Microphone Sets



WS-5225



Combination includes:

- WM-5225
- WT-5810

WS-5265



Combination includes:

- WM-5265
- WT-5810

WS-5325H



Combination includes:

- WM-5325
- WH-4000H
- WT-5810

WS-5325U



Combination includes:

- WM-5325
- YP-M5300
- WT-5810

WS-5325M



Combination includes:

- WM-5325
- YP-M5310
- WT-5810



Like us on Facebook
facebook.com/TOAAsiapacific



TOA Electronics Pte Ltd

www.toa.com.sg

Specifications are subject to change without notice.
Printed in Singapore (65) 865-1022-01